

Product Specification

Number: L-KLS21-RF4KEY104S
Name: Remote Control
Specification: Learning code,433.92MHz
Customer: D02
Date: 2020-11-03

Customer Signature:



NINGBO KLS ELECTRONIC CO; LTD

Tel : 0086-574-86828566

Fax : 0086-574-86824882

ADD : NO. 8-1, RONGXIA RD. XIAPU SHANQIAN
INDUSTRIAL ZONE BEILUN NINGBO ZHEJIANG.

Compi	Check	Review	Approva
Jenny	Jack.C		

Part name		Date	2020-11-03
Part number	L-KLS21-RF4KEY104S	Edition	V1
Department	Remote Control	Page	3 / 3



1. Chips could be copied

2260(all manufacturers);2262(All manufacturers);PT2264, 5326(All manufacturers); SC5262, HT600, HT680, HT6207, HT6010, HT6012, HT6014, SMC918series, 527(All manufacturers);1527(All manufacturers);2240(All manufacturers);HCS101, HCS200\HCS201(part code),HCS300\HCS301(Part code), part single chip microcomputer.....

2.Code cleaning method:

Press the unlock button and lock button at the same time(some shells are the up button and down button), after the LED indicator light flashes three times, loosen any one of the buttons while the other is kept pressing, then push the released button three times, the LED indicator will enter into the fast flashing status. At this time all the memory data is cleared, the cleaned remote control will not have lighting LED indicator no matter which button you press.

Part name		Date	2020-11-03
Part number	L-KLS21-RF4KEY104S	Edition	V1
Department	Remote Control	Page	2 / 3

3. Copy method

One hand keeps the original remote controller, while another keeps the copy remote control, the two remote controls should be placed as closely as possible (the ideal situation is to put the two remote controls on the desktop side by side with zero distance), respectively press down the copy button, when the LED indicator light flashes quickly after three flashes, this copy is successful, other key operating methods are the same. Some remote control has a smaller transmitting power, so the original remote control should be placed back to the copy remote control to be operated. For the presence of noise, it should avoid interference to operate, If the copy is not successful, it should recopy after clearing code.

Attention:

Your original remote control must be able to work and the same as our remote control frequency

4. The features of new copy remote control

The four buttons could respectively copy four different types of chips, That is a remote control can operate four different types of facilities. T Faster copy data speed, not easy losing code, far distance.